

# JWT6012

## Double Temperature Controller

- NO and NC in one casing
- Separate adjustable temperatures
- High switching capacity
- Terminals easily accessible
- Clip fixing



## Two thermostats in one casing:

A thermostat with two temperature settings

Thermostat (contact breaker, normally closed) for regulating heaters Thermostat (contact make, normally open) for regulating filter fans and heat exchangers or switching signal devices when temperature limit has been exceeded.

Heaters and cooling equipment can be switched independently from each other with a temperature offset as opposed to the usual change-over contacts.



### **Technical Specification**

Temperature Range

**Switching Temperature** 

Tolerance

Sensing Element

Maximum Switching

Capacity

**Electrical Connection** 

Installation

Operating / Storage areas

**Terminal** 

Weight

Size

0~60 °C 7K (± 4K)

**Bimetallic** 

250VAC, 10 (2) A / 120VAC, 15 (2) A / DC 30W

4 pole 2.5mm, 0.8Nm

35mm DIN rail mounting

-5 °C to + 80 °C

UL94Vo

90a

69\*50\*46 mm

#### SENSING TECHNOLOGY CORPORATION

457-B Boni Avenue, New Zaniga, Mandaluyong City, Philippines 1550

Tel. no.: (63) 2 8532 0088 Fax: (63) 2 8531 7387 Email: sales@heatsenze.com Website: www.heatsenze.com